



The MT-X Expansion Box can be added to any A-16II Personal Mixer—the industry standard solution for delivering high quality monitoring control on stage and in the studio. The MT-X provides robust protection to the Personal Mixer’s case and connectors and also provides additional audio connectivity options.

All connectors are located on the underside of the MT-X, with an internal wire harness that connects to the A-16II audio output jack and A-Net® input jack. Audio connections include both 1/8-inch and 1/4-

inch stereo headphone jacks, as well as separate XLR left/right audio outputs, simplifying connections to nearly any monitoring device. The A-Net In on the MT-X utilizes a heavy-duty locking EtherCon® connector.

The MT-X Expansion Box attaches to any A-16 or A-16II Personal Mixer using the same mounting holes used by the MT-1 Mic Mount, which is required for the MT-X. Personal Mixers equipped with an MT-X must be powered over the Cat-5 cable from an A-16D or A-16D Pro A-Net distributor.

PRODUCT HIGHLIGHTS

- Ruggedizes A-16II Personal Mixer
- Provides extra protection against cable pulls
- Integrates additional audio connection options
- Mounts to MT-1 Mic Mount bracket

MT-X EXPANSION BOX SPECIFICATIONS

Audio Outputs	1/4" TRS stereo, headphone or line level (dual mono) 1/8" TRS stereo, headphone or line level (dual mono) XLR left/right audio outputs (dual mono, unbalanced)
A-Net I/O	1 A-Net In, EtherCon RJ45 connectors
Mounting	Requires MT-1, and attaches to the same mounting holes on the Personal Mixer; longer screws included
Dimensions	10.6" (269 mm) wide x 1.44" (36.8 mm) deep; 2.38" (50.8 mm) high
Weight	1.0 lb. (0.45 kg)
<i>All Aviom products are designed and manufactured in the USA.</i>	

1157 Phoenixville Pike, Suite 201 • West Chester, PA 19380
Voice: +1 610.738.9005 • Fax: +1 610.738.9950 • www.Aviom.com